




■ Quick selection guide



General purpose fuses

• Fuse-link

Illustration	Ratings		Current (A)	Type	Ordering code	Mass (kg)	Applicable fuse-holder	
	Voltage (kV)	Interrupting capacity (kA)					Indoor use Type	Outdoor use Type
 SD-423 SCF-6/30 30A	7.2	40 (500MVA)	5	SCF-6/5	HF2S-005	1.3	SCHA-6 SCHIII-6	—
			10	SCF-6/10	HF2S-010	1.3		
			20	SCF-6/20	HF2S-020	1.3		
			30	SCF-6/30	HF2S-030	1.3		
			40	SCF-6/40	HF2S-040	1.3		
			20 (250MVA)	50	SCF-6/50	HF2S-050		
 SD-424 HF337E/3/10 10A HF338E/3/100 100A	3.6	40 (250MVA)	5	HF337E/3/5	HF1A-005	1.0	HF340/6a HF340III/6a	HF326C/6a
			10	HF337E/3/10	HF1A-010	1.0		
			20	HF338E/3/20	HF1E-020	2.5		
			30	HF338E/3/30	HF1E-030	2.5		
			40	HF338E/3/40	HF1E-040	2.5		
			50	HF338E/3/50	HF1E-050	2.5		
			75	HF338E/3/75	HF1E-075	2.5		
			100	HF338E/3/100	HF1E-100	2.5		
			150	HF338E/3/150	HF1E-150	4.0		
			200	HF338E/3/200	HF1E-200	4.0		
			400	HF338E/3/400*	HF1E-400	6.5		
			 SD-425 HF338E/6/400 400A	7.2	40 (500MVA)	5		
10	HF337E/6/10	HF2A-010				1.0		
20	HF338E/6/20	HF2E-020				2.5		
30	HF338E/6/30	HF2E-030				2.5		
40	HF338E/6/40	HF2E-040				3.0		
50	HF338E/6/50	HF2E-050				3.0		
75	HF338E/6/75	HF2E-075				3.0		
100	HF338E/6/100	HF2E-100				3.0		
150	HF338E/6/150	HF2E-150				3.0		
200	HF338E/6/200*	HF2E-200				3.0		
31.5 (390MVA)	400	HF338E/6/400*	HF2E-400	6.5				

Note: * Back up fuse.

• Fuse-holder

Illustration	Rated voltage (kV)	Usage	Poles	Type	Ordering code	Mass (kg)		
 SD-428 HF	3.6/7.2	Indoor use	1	HF340/6a	HE3E	3.0		
			1	HF340/6b	HE3F	3.5		
			1	HF323/6e	HE3U	16.5*		
			3	HF340III/6a	HE3P	7.0		
			3	HF340III/6b	HE3Q	8.0		
 SD-422 SCHIII-6	3.6/7.2	Outdoor use	1	HF326C/6a	HE3R	21.5*		
			1	HF326C/6b	HE3K	22.0*		
			1	HF326CII/6b	HE3L	24.0*		
	7.2	Indoor use	1	SCHA-6	HE3S	3.3		
			3	SCHIII-6	HE3T	7.0		

Note: Mass does not include fuse-link.
 * With porcelain insulator.